

PRODUCT SPECIFICATIONS FOR DE200 GC (60 HZ)

GENERATOR SET SPECIFICATIONS

Minimum Rating	175 ekW
Maximum Rating	175 ekW
Emissions/Fuel Strategy	Non Regulated
Voltage	220 to 480 Volts
Frequency	60 Hz
Speed	1800 rpm
Duty Cycle	Standby

ENGINE SPECIFICATIONS

Engine Model	C7.1 I-6, 4-Cycle Diesel
Bore	105 mm
Stroke	135 mm
Displacement	7 l
Compression Ratio	16.0:1
Aspiration	Turbocharged Air To Air Charge Cooled
Fuel System	Inline
Governor Type	Mechanical

GENERATOR SET DIMENSIONS

Length - Maximum	3325 mm
Width - Maximum	1134 mm
Height - Maximum	1666 mm

Dry Weight - Genset (maximum)

1931 kg

DE200 GC (60 HZ) STANDARD EQUIPMENT

ENGINE

C7.1, Inline 6 Cylinder, 4 Stroke Diesel

CONTROL PANELS

GCCP 1.1

ENCLOSURE

Cat GC Enclosure

GOVERNOR

Mechanical Governor

ALTERNATOR

A Frame Standard Alternator

FUEL STORAGE

Single Wall 8 Hour Tank

AIR, COOLING & EXHAUST

Enclosure Silencer

GENERAL

Engine and alternator pre-paint, Caterpillar Yellow

DE200 GC (60 HZ) OPTIONAL EQUIPMENT

CERTIFICATION

Certificate of Conformance

Australia, CIS, Gulf Certification

AUXILIARY SUPPLY VOLTAGE

120V

ALTERNATOR REQUIREMENTS

Space Heater

GENSET CONTROL

Battery Charger

Panel Mounted Audible Alarm

Volt Free Contacts for Genset Running

Volt Free Contacts for Common Alarm

Earth Fault

Emergency Stop with Key

USB to RS485 Communications Device

Coolant Heater

Low Coolant Level Shutdown

Battery

Standby Pack (Smart Jacket Water Heater, Battery Charger)

FUEL STORAGE

Dual Wall 8 Hour Tank

Single Wall Tank With Containment

Low Fuel Level Shutdown

Low Fuel Level Alarm

High Fuel Level Alarm

TESTING & PACKAGING

PGS Test Report @ 1.0PF

PGS Test Report @ 0.8PF

CIRCUIT BREAKER

3 Pole Circuit Breaker 630A

4 Pole Circuit Breaker 200A

4 Pole Circuit Breaker 250A

3 Pole Circuit Breaker 250A

3 Pole Circuit Breaker 200A

4 Pole Circuit Breaker 400A

4 Pole Circuit Breaker 630A

Circuit Breaker Padlock

Neutral Earth Link

Overload via Alarm Switch on Breaker

3 Pole Circuit Breaker 400A

3 POLE CIRCUIT BREAKER 400A

